



Add IPC Through Local Interface

Version 1.0.1

How to add IP camera in DVR/NVR

Step 1 - Go to, **Main Menu** → **Camera** and you will get interface as shown in below image.



Step 2 - Click on **REMOTE DEVICES** and you will get interface as shown below image then click IP Search option to search all IP camera of network.

| ★CP PLUS | | | | | | | / | |
|-----------------|-----------------|--------|-------------------|----------|-------|--------------|-------------|------------|
| REMOTE DEVICE | | | | | | | | |
| REMOTE | | | | | | | | |
| STATUS | | | | | | 🗌 Un | initialized | Initialize |
| FIRMWARE | 0 Edit | | Status IP Address | | ress | Manufacturer | | |
| | | | | | | | | |
| | | | | | | | | |
| | | | | | | | | |
| | arch network de | /ices | | | | | | |
| | 1 | | | | | | | |
| | | | | | 1 | | | • |
| | IP Search | Add | Mar | nual Add | | Show F | -ilter No | ne 👻 |
| | | | | | | | | |
| | Added Devid | e – | | _ | _ | _ | _ | |
| | Channe | I Edit | Delete | Status | IP Ad | dress | Port | Devi |
| | | | | | | | | |
| | | | | | | | | |
| | ۹ [| | | |] | | | • |
| | Delete |) | | | (| EXPO | RT | IMPORT |
| | | | | | | | | |
| | | | | | | | | |
| | | | | | | | | |

Step 3 - Double click an IP address or check one IP address and then click Add button.

| | | | | | | | ~ | |
|---------------------|---------------|----------|----------|----------------------------------|-------|------------|-----------------|------------|
| REMOTE DEVICE | | | | | | | | |
| REMOTE | | | | | | | | |
| STATUS | 1. Select a I | | | | | <u>о</u> | | |
| | ↓ <u>↑</u> | | _ | | | | in nualizeu | Initialize |
| FIRIVIWARE | 19 | 19 Edit | | IP Address | | Manu | lfacturer | A |
| | 1 | ę | 172.16.0 | | 0.72 | D | | |
| | 2 | 2 | | 1/2.16.2.1/ CF 172.16.2.98 CF | | CP | PLUS | CP-U |
| | 3 | <u>e</u> | | | | PLUS | CFL | |
| | 5 | | | 172.10. | 2.90 | CP | PLUS | CE |
| | 6 | 2 | | 172.16.2.122 | | Di | ahua | |
| | 7 | 2 | | 172.16.2.134 CPPL | | PLUS | CP | |
| | 0 | • | | 170 16 0 140 | | Onvit | | - nn - |
| | | | | | | Chau | Eilten N | |
| 2 Click to add came | | | | hual Add | | Show | | one 👻 |
| | Added De | vice 🛑 | | | | | | |
| | Channel Edit | | Delete | Status | IP Ac | IP Address | | Devi |
| | 4 | 1 | × | 0 | 172.1 | 6.2.101 | 25001 | CP2K0248 |
| | | | | | | | | |
| | | | | | | | | |
| | • | | | | 1 | | | • |
| | Delete | | | | - 1 | EXPO | | IMPORT |
| | | - + | | | | | | |
| | | | | | | | | |
| | | | | | | | | |
| | | | | | | | | |
| | | | | | | | | |

Step 4 - Click on edit icon to modify any details of camera, if other than default and then click on OK to save the setting.

| | La | | | | 1 | |
|----------------|------------|-----|----|----|-------|--|
| Edit | | | | | | |
| Channel | 4 | - | | | | |
| Manufacturer | CPPLUS | | | | | |
| Protocol | CPUNC | • | | | | |
| IP Address | 172.16.2.1 | 101 | | | | |
| TCP Port | 25001 | | | | | |
| Username | admin | | | | | |
| Password | | ••• | | | | |
| Remote Channel | 1 | | | | | |
| Decoder Buffer | Default | | | | | |
| | | | | | | |
| Сору | | | OK | DC | Cance | |

Step 5 – Once the camera status becomes Online. You can check the live preview of cameras.

Thank You for Choosing CP Plus!!

